

BOX_00 **(RJ1000)** **Item Type:** Route **Type Class:** If Then

Route Details: 01 Box = BOX_00, BOX_10, BOX_20, BOX_30, BOX_40, BOX_50, BOX_60, BOX_70

02 Loop = LOOP_10

03 End Loop = END_LP10

04 Single Select = RJ10, RJ20, RJ30, RJ40, RJ50, RJ55, RJ60, RJ70, RJ80, RJ90, RJ100, RJ130

14 Regular Date Entry = RJ120_01, RJ120_02, RJ120_03

19 Numeric Field = RJ110

20 OS Text Field = RJ50OS, RJ55OS, RJ130OS

BOX_10 **(RJ1001)** **Item Type:** Route **Type Class:** If Then

Route Details: Context header display instructions:
Display FULLNAME, JobsEstbName, JobStartMM/DD/YYYY, JobStopMM/DD/YYYY

BOX_20 **(RJ1005)** **Item Type:** Route **Type Class:** If Then

Route Details: If information about at least one current job was collected for person during the previous round, ask the review of employment information (RJ) section. That is, if:
-is rounds 2-5,

- Person not added to the RU this round,
- Person was = or > 16 years old or in age categories 4-9 during the previous round, and
- Person had a job with a job type set as 'current main' or 'current miscellaneous job within reference period' during the previous round, (PR_JobTP=CURRENT MAIN OR PR_JobTP=CURRENT MISC

Continue with LOOP_10.

Otherwise, skip the RJ section, that is, go to BOX_70.

LOOP 10 **(RJ1010)** **Item Type:** Route **Type Class:** Begin Loop

Route Details: For each element in PERSON'S-JOBS-ROSTER, ask BOX_30 - END_LP10.

Loop definition: LOOP_10 reviews and updates information about current jobs collected during the previous round. This loop cycles on the jobs that meet the following conditions:

Job type is set as either 'current main' (PR_JobTP=CURRENT MAIN), or 'current miscellaneous job within reference period' during the previous round (PR_JobTP=CURRENT MISC)

Navigator details: LOOP_10 uses BOX_30 to control the flow of the loop.

BOX 30 **(RJ1020)** **Item Type:** Route **Type Class:** If Then

Route Details: If job set as 'current main', (PR_JobTP=CURRENT MAIN) continue with RJ10.

Otherwise (if job type set as 'CURRENT MISCELLANEOUS JOB WITHIN REFERENCE PERIOD')(PR_JobTP=CURRENT MISC) go to RJ60.

RJ20	(RJ1045)	BLAISE NAME: MainJob		
Item Type:	Question	Field kind: Datafield	ArrayMin:	Min value:
Type Class:	Enumerated	Field Size:		
Answer Type:	TYESNO	Answers allowed: 1	ArrayMax:	Max value:

Help Available (MainJobHelp) Show Card () Look Up File ()

Context Header: {PERSON'S FIRST MIDDLE AND LAST NAME} {JobsEstbName}
 {JobStartMM/DD/YYYY}
 {JobStopMM/DD/YYYY}

Question Text:

{Is/Was} {JobsEstbName} still {your/{PERSON}'s} main job or business?

HELP : F1

Responses: YES 1
 NO 2
 REFUSED RF
 DON'T KNOW DK

Programmer Instructions: If job being asked about set as 'SELF-EMPLOYED' (SelfEmp=SelfEmpl) go to RJ40. Else go to RJ30

 If RJ20 coded '1' (YES), DK, or RF, set job type to 'CURRENT MAIN JOB WITHIN REFERENCE PERIOD' (JobTp=CURRENT MAIN)

 If RJ20 coded '2' (NO), set job type to 'CURRENT MISCELLANEOUS JOB WITHIN REFERENCE PERIOD' (JobTp=CURRENT MISC)

Display Instructions: Display 'Is' if not round 5. Display 'Was' if round 5.

RJ30	(RJ1050)	BLAISE NAME: ChngWageAmt		
Item Type:	Question	Field kind: Datafield	ArrayMin:	Min value:
Type Class:	Enumerated	Field Size:		
Answer Type:	TYESNO	Answers allowed: 1	ArrayMax:	Max value:

Help Available () Show Card () Look Up File ()

Context Header: {PERSON'S FIRST MIDDLE AND LAST NAME} {JobsEstbName}
 {JobStartMM/DD/YYYY}
 {JobStopMM/DD/YYYY}

Question Text:

{During our last interview, we recorded that {you/{PERSON}} made {PR_SalaryDisplay.} {Since {PREV RD INT DT}, has/Between {START DATE} and {END DATE}, was} there {been} any change in the amount {you/{PERSON}} {{make/makes}/made} through{JobsEstbName}?

INTERVIEWER NOTE: THIS INCLUDES CHANGES IN BOTH DIRECTIONS.

Responses:	YES	1	BOX_40	(RJ1065)
	NO	2	RJ40	(RJ1070)
	REFUSED	RF	RJ40	(RJ1070)
	DON'T KNOW	DK	RJ40	(RJ1070)

Display Instructions: {During our last interview, we recorded that {you/{PERSON}} made {PR_SalaryDisplay.}: Display sentence if PR_SalaryDisplay≠EMPTY.

{Since {PREV RD INTR DT}, has/Between {START DATE}} and {END DATE was}: DISPLAY 'Since {PREV RD INTDT}, has' if not round 5. Display 'Between {START DATE} and {END DATE}, was' if round 5.

{START DATE}: Display the round 5 reference period for start date for this person.

{END DATE}: Display the round 5 reference period end date for this person.

{been}: Display 'been' if not round 5. Otherwise, use a null display.

{{make/makes}/made}: Display '{make/makes}' if not round 5. Display 'made' if round 5. For {PREV RD INT DT}, display the interview date of the previous round. (Preload.RUEndM, RUEndD, RUEndY).

BOX 40 **(RJ1065)** **Item Type:** Route **Type Class:** If Then

Route Details: Ask the Employment Wage (EW) section.

At completion of Employment Wage (EW) section, continue with RJ40.

RJ40 **(RJ1070)** **BLAISE NAME:** StillWorkFTPT
Item Type: Question **Field kind:** Datafield **ArrayMin:** **Min value:**
Type Class: Enumerated **Field Size:**
Answer Type: TYESNO **Answers allowed:** 1 **ArrayMax:** **Max value:**

Help Available () Show Card () Look Up File ()

Context Header: {PERSON'S FIRST MIDDLE AND LAST NAME} {JobsEstbName}
 {JobStartMM/DD/YYYY}
 {JobStopMM/DD/YYYY}

Question Text:

During our last interview on {PREV RD INTV DT}, we recorded that {you/{PERSON}} worked {full-time/part-time}, that is {35 hours or more/less than 35 hours} per week at {JobsEstbName}. {{Do/Does}/Did} {you/he/she} still work {35 hours or more/less than 35 hours} per week at {JobsEstbName} {on {END DATE}}?

Responses: YES 1 BOX_50 (RJ1105)
 NO 2
 REFUSED RF BOX_50 (RJ1105)
 DON'T KNOW DK BOX_50 (RJ1105)

Programmer Instructions: If the classification of number of hours worked per week has changed since the previous round, that is,:

If coded '2' And PR_FTPTStatus=PART TIME

- Set FTPTStatus=FULL TIME (part-time to full time)
- Otherwise set FTPTStatus=PART TIME

Then go to RJ50.

If Coded '2' And PR_FTPTStatus=FULL TIME

- Set FTPTStatus=PART TIME (full-time to part-time)
- Otherwise set FTPTStatus=FULL TIME

Then go to RJ55.

Display Instructions:

For {PREV RD INTV DT} display the interview date of the previous round.
Preload.RUEndM, RUEndD, RUEndY).

Display 'full-time' if PR_FTPTStatus=FULL TIME

Display 'part-time' if PR_FTPTStatus=PART TIME.

Display '{Do/Does}' if not round 5. Display 'did' if round 5.

Display '35 hours or more' if if PR_FTPTStatus=FULL TIME

Display 'less than 35 hours' if PR_FTPTStatus=PART TIME

Display 'on {END DATE}' if round 5, displaying the round 5 end date for this person for 'END DATE. Otherwise, use null display.

RJ50 **(RJ1075)** **BLAISE NAME:** WhyChngPTToFT
Item Type: Question **Field kind:** Datafield **ArrayMin:** **Min value:**
Type Class: Enumerated **Field Size:**
Answer Type: TY_CHANGE **Answers allowed:** 1 **ArrayMax:** **Max value:**

Help Available () Show Card () Look Up File ()

Context Header: {PERSON'S FIRST MIDDLE AND LAST NAME} {JobsEstbName}
 {JobStartMM/DD/YYYY}
 {JobStopMM/DD/YYYY}

Question Text:

What is the main reason {you/{PERSON}} changed from part-time to full-time at {(JobsEstbName)}?

Responses: CHANGE IN SCHEDULE OR SHIFT 1 BOX_50 (RJ1105)
 CHANGE IN PAY 2 BOX_50 (RJ1105)
 BENEFITS/HEALTH INSURANCE 3 BOX_50 (RJ1105)
 FAMILY, SCHOOL, TEMPORARY LEAVE..... 4 BOX_50 (RJ1105)
 OTHER-SPECIFY 91 RJ50OS (RJ1080)
 REFUSED RF BOX_50 (RJ1105)
 DON'T KNOW DK BOX_50 (RJ1105)

Display Instructions: Display RJ50 and RJ50OS on the same form pane.

RJ50OS **(RJ1080)** **BLAISE NAME:** WhyChngPTToFTOS
Item Type: Question **Field kind:** Datafield **ArrayMin:** **Min value:**
Type Class: String **Field Size:** 25
Answer Type: {Continuous Answer.} **Answers allowed:** 1 **ArrayMax:** **Max value:**

Help Available () Show Card () Look Up File ()

Question Text:

SPECIFY: MAIN REASON

Responses: 1 BOX_50 (RJ1105)
 REFUSED RF BOX_50 (RJ1105)
 DON'T KNOW DK BOX_50 (RJ1105)

Display Instructions: Display RJ50 and RJ50OS on the same form pane.

RJ55	(RJ1081)	BLAISE NAME: WhyChngFTToPT		
Item Type:	Question	Field kind: Datafield	ArrayMin:	Min value:
Type Class:	Enumerated	Field Size:		
Answer Type:	TREASONFULLTTO	Answers allowed: 1	ArrayMax:	Max value:

Help Available () Show Card () Look Up File ()

Context Header: {PERSON'S FIRST MIDDLE AND LAST NAME} {JobsEstbName}
 {JobStartMM/DD/YYYY}
 {JobStopMM/DD/YYYY}

Question Text:

What is the main reason {you/{PERSON}} changed from full-time to part-time at {JobsEstbName}?

Responses:	HOURS CUT, BUSINESS SLOW	1	BOX_50	(RJ1105)
	CHANGE IN SCHEDULE OR SHIFT	2	BOX_50	(RJ1105)
	ILLNESS, INJURY, HEALTH PROBLEM	3	BOX_50	(RJ1105)
	FAMILY, SCHOOL, TEMPORARY LEAVE.....	4	BOX_50	(RJ1105)
	OTHER-SPECIFY	91	RJ55OS	(RJ1082)
	REFUSED	RF	BOX_50	(RJ1105)
	DON'T KNOW	DK	BOX_50	(RJ1105)

Display Instructions: Display RJ55 and RJ55OS on the same form pane.

Programmer Instructions: If RJ60 coded '1' (YES) Set JobTp=CURRENT MISC
If RJ60 coded '2' (NO), 'DK' or 'RF' Set JobTp=FORMER MISC

Display Instructions: For {PREV RD INTV DT} display the interview date of the previous round
(Preload.RUEndM, RUEndD, RUEndY).
Display '{Do/Does}' if not round 5. Display 'Did' if round 5.
For {on {END DATE}}: display if round 5. Otherwise, use a null display.
For {END DATE}: display the round 5 reference period end date for this person.

BOX 50 **(RJ1105)** **Item Type:** Route **Type Class:** If Then

Route Details: If RJBox50Flag=1 (INSURANCE AT END OF PREVIOUS ROUND) then go to BOX_60
If RJBox50Flag=2 (INSURANCE ENDED IN PREVIOUS ROUND BUT OFFERED NOT TAKEN ON FIRST JOB REPORT) then go to RJ70
If RJBox50Flag=3 (NO INSURANCE AT END OF PREVIOUS ROUND) then go to RJ80
If RJBox50Flag=4 (MILITARY CURRENT MAIN JOB) go to END_LP10

Note: RJBox50Flag is set in inter-round processing (MHOP)

RJ70 **(RJ1110)** **BLAISE NAME:** OffrdHINowTake
Item Type: Question **Field kind:** Datafield **ArrayMin:** **Min value:**
Type Class: Enumerated **Field Size:**
Answer Type: TYESNO **Answers allowed:** 1 **ArrayMax:** **Max value:**

Help Available (HLTHINSHelp) Show Card () Look Up File ()

Context Header: {PERSON'S FIRST MIDDLE AND LAST NAME} {JobsEstbName}
 {JobStartMM/DD/YYYY}
 {JobStopMM/DD/YYYY}

Question Text:

During our last interview on {PREV RD INTV DT}, we recorded that {you/{PERSON}} {were/was} offered health insurance through {JobsEstbName} but chose not to take that insurance. {{Do/Does}/Did} {you/he/she} {now} have health insurance through {JobsEstbName} {on {END DATE}}?

HELP: F1

Responses: YES 1 BOX_60 (RJ1150)
 NO 2 RJ90 (RJ1120)
 REFUSED RF RJ90 (RJ1120)
 DON'T KNOW DK RJ90 (RJ1120)

Programmer Instructions: If coded '1' (YES), set this jobholder-job pair as 'PROVIDES HEALTH INSURANCE'(EmpHI=YES) and to be asked about in the health insurance section.

 If coded '2' (NO), 'RF' (REFUSED), or 'DK' (DON'T KNOW), set this jobholder-job pair as not providing health insurance (EmpHI=EMPTY).

Display Instructions: {PREV RD INTV DT}: display the interview date of the previous round (Preload.RUEndM, RUEndD, RUEndY).

 Display '{Do/Does}' if not round 5. Display 'Did' if round 5. Display 'now' if not round 5. if round 5, display null.
 For {on {END DATE}}: display if round 5. Otherwise use a null display.

 For {END DATE}: display the round 5 reference period end date for this person.

RJ80 **(RJ1115)** **BLAISE NAME:** NowOffrdTakeHI
Item Type: Question **Field kind:** Datafield **ArrayMin:** **Min value:**
Type Class: Enumerated **Field Size:**
Answer Type: TYESNO **Answers allowed:** 1 **ArrayMax:** **Max value:**

Help Available (HLTHINSHelp) Show Card () Look Up File ()

Context Header: {PERSON'S FIRST MIDDLE AND LAST NAME} {JobsEstbName}
 {JobStartMM/DD/YYYY}
 {JobStopMM/DD/YYYY}

Question Text:

During our last interview on {PREV RD INTV DT}, we recorded that {you/{PERSON}} {were/was} not {offered/receiving} health insurance through {JobsEstbName}. {{Do/Does}/Did} {you/he/she} {now} have health insurance through{JobsEstbName} {on {END DATE}}?

HELP: F1

Responses: YES 1 BOX_60 (RJ1150)
 NO 2 RJ90 (RJ1120)
 REFUSED RF BOX_60 (RJ1150)
 DON'T KNOW DK BOX_60 (RJ1150)

Programmer Instructions: If coded '1' (YES) flag this jobholder-establishment pair as 'PROVIDES HEALTH INSURANCE' (EmpHI=YES) and to be asked about in the health insurance section.

If coded '2' (NO), 'RF' (REFUSED), or 'DK' (DON'T KNOW), set this jobholder-job pair as not providing health insurance (EmpHI=EMPTY).

Display Instructions: {PREV RD INTV DT}: display the interview date of the previous round (Preload.RUEndM, RUEndD, RUEndY).

Display 'offered' if PR_EmpHI=EMPTY and PR_OffrdHIChoseNot <> 1 and PR_ConfCovd = EMPTY. Otherwise, display 'receiving'.

Display '{Do/Does}' if not round 5. Display 'Did' if round 5. Display 'now' if not round 5. If round 5, display null.

For {on {END DATE}}: display if round 5. Otherwise, use a null display.

For {END DATE}: display the round 5 reference Period end date for this person.

RJ90 **(RJ1120)** **BLAISE NAME:** OffrdHIThruJob
Item Type: Question **Field kind:** Datafield **ArrayMin:** **Min value:**
Type Class: Enumerated **Field Size:**
Answer Type: TYESNO **Answers allowed:** 1 **ArrayMax:** **Max value:**

Help Available (HLTHINSHelp) Show Card () Look Up File ()

Context Header: {PERSON'S FIRST MIDDLE AND LAST NAME} {JobsEstbName}
 {JobStartMM/DD/YYYY}
 {JobStopMM/DD/YYYY}

Question Text:

{Were/Was} {you/{PERSON}} offered health insurance through {JobsEstbName}?

HELP: F1

Responses: YES 1 BOX_60 (RJ1150)
 NO 2 RJ100 (RJ1125)
 REFUSED RF BOX_60 (RJ1150)
 DON'T KNOW DK BOX_60 (RJ1150)

**Display
Instructions:**

<u>RJ100</u>	<u>(RJ1125)</u>	<u>BLAISE NAME:</u> RvwAnyOffrdHI		
Item Type:	Question	Field kind: Datafield	ArrayMin:	Min value:
Type Class:	Enumerated	Field Size:		
Answer Type:	TYESNO	Answers allowed: 1	ArrayMax:	Max value:

Help Available () Show Card () Look Up File ()

Context Header: {PERSON'S FIRST MIDDLE AND LAST NAME} {JobsEstbName}
 {JobStartMM/DD/YYYY}
 {JobStopMM/DD/YYYY}

Question Text:

Was health insurance offered to any employees at {JobsEstbName}?

Responses:	YES	1	BOX_60	(RJ1150)
	NO	2	BOX_60	(RJ1150)
	REFUSED	RF	BOX_60	(RJ1150)
	DON'T KNOW	DK	BOX_60	(RJ1150)

**Display
Instructions:**

<u>BOX 60</u>	<u>(RJ1150)</u>	Item Type: Route	Type Class: If Then
----------------------	------------------------	-------------------------	----------------------------

Route Details: If employer set as 'SELF-EMPLOYED', (SelfEmp=SelfEmpl) continue with RJ110.
 Otherwise, Set EmpEstm=PR_EmpEstm and go to END_LP10.

RJ110 **(RJ1155)** **BLAISE NAME:** RvwTotNumEmp
Item Type: Question **Field kind:** Datafield **ArrayMin:** **Min value:** 1
Type Class: Integer **Field Size:** 5
Answer Type: {Continuous Answer.} **Answers allowed:** 1 **ArrayMax:** **Max value:** 99999

Help Available () Show Card () Look Up File ()

Context Header: {PERSON'S FIRST MIDDLE AND LAST NAME} {JobsEstbName}
 {JobStartMM/DD/YYYY}
 {JobStopMM/DD/YYYY}

Question Text:

{During our last interview we recorded that { PR_TotNumEmp} {employee/employees}, including {you/{PERSON}}, worked at {JobsEstbName}.}

What is the total number of employees who worked at the business {last week/{on {END DATE}}}? Be sure to include the owner and all other household members that may {work/have worked} there.

ENTER AT LEAST 1 TO COUNT THE OWNER. ENTER NUMBER OF EMPLOYEES

Responses: 1 END_LP10 (RJ1175)
 REFUSED RF END_LP10 (RJ1175)
 DON'T KNOW DK END_LP10 (RJ1175)

**Programmer
Instructions:**

Range check:
Numeric value entered must be equal to or > 1. If '0' is entered, display the following message: "Since {you/{PERSON'S FIRST MIDDLE AND LAST NAME}} {is/are} the owner, I am going to enter 1 to count {you/him/her}. ENTER 1 AT RJ110 (RvwTotNumEmp) FOR NUMBER OF EMPLOYEES TO CONTINUE."

Set TotNumEmp=the value entered at RJ110.

If the value entered for the number of employees=1 set EmpEstm= '1'
If the value entered for the number of employees=2-9, inclusive, set EmpEstm= '2-9'
If the value entered for the number of employees=10-25, inclusive, set EmpEstm= '10-25'
If the value entered for the number of employees=26-50, inclusive, set EmpEstm= '26-50'
If the value entered for the number of employees=51-100, inclusive, set EmpEstm= '51-100'
If the value entered for the number of employees=101-200, inclusive, set EmpEstm= '101-200'
If the value entered for the number of employees =201-500, inclusive, set EmpEstm='201-500'

If the value entered for the number of employees is > 500 set EmpEstm='500+'
If coded 'RF' or 'DK' retain EmpEstm used during the previous round

**Display
Instructions:**

{During our last interview we recorded that { PR_TotNumEmp} {employee/employees}, including {you/{PERSON}}, worked at {JobsEstbName}.}: display sentence if PR_TotNumEmp was not coded 'RF' or 'DK' during the previous round for the job being asked about. Otherwise, use a null display.

Display 'employee' if PR_TotNumEmp=1 otherwise display 'employees'.

Display 'on {END DATE}' if round 5. Otherwise, display 'last week'. Display 'work' if not round 5. Otherwise, display 'have worked'.

For {END DATE}: display the round 5 reference period end date for this person.

RJ120_01 **(RJ1160)** **BLAISE NAME:** RvwJobStopMM
Item Type: Question **Field kind:** Datafield **ArrayMin:** **Min value:** 1
Type Class: Integer **Field Size:** 2
Answer Type: {Continuous Answer.} **Answers allowed:** 1 **ArrayMax:** **Max value:** 12

Help Available () Show Card () Look Up File ()

Context Header: {PERSON'S FIRST MIDDLE AND LAST NAME} {JobsEstbName}
 {JobStartMM/DD/YYYY}
 {JobStopMM/DD/YYYY}

Question Text:

When did {you/{PERSON}} stop working at {JobsEstbName} for pay?
 {IF JOB ENDED AFTER DECEMBER 31, {YEAR}, BACKUP TO {RJ10/RJ60} AND SELECT 'YES'.}
 ENTER MONTH.

Responses: ----- 1 RJ120_02 (RJ1162)
 REFUSED ----- RF RJ120_02 (RJ1162)
 DON'T KNOW ----- DK RJ120_02 (RJ1162)

Programmer Instructions: Set JobStopMM

Display Instructions: Display RJ120_1, RJ120_2, and RJ120_3 on the same form pane.
 Display 'IF JOB ENDED... SELECT 'YES'.' if round 5. Otherwise, use a null display.
 Display 'RJ10' if looping on 'CURRENT MAIN JOB'(PR_JobTP=CURRENT MAIN). Display 'RJ60'
 if looping on 'CURRENT MISCELLANEOUS JOB WITHIN REFERENCE PERIOD'
 (PR_JobTP=CURRENT MISC)
 Note: For specification purposes only; CAPI handles automatically: 'YEAR' in question text is
 second calendar year of panel.

RJ120_02 **(RJ1162)** **BLAISE NAME:** RvwJobStopDD
Item Type: Question **Field kind:** Datafield **ArrayMin:** **Min value:** 1
Type Class: Integer **Field Size:** 2
Answer Type: {Continuous Answer.} **Answers allowed:** 1 **ArrayMax:** **Max value:** 31

Help Available () Show Card () Look Up File ()

Context Header: {PERSON'S FIRST MIDDLE AND LAST NAME} {JobsEstbName}
 {JobStartMM/DD/YYYY}
 {JobStopMM/DD/YYYY}

Question Text:

[When did {you/{PERSON}} stop working at {JobsEstbName} for pay?
 {IF JOB ENDED AFTER DECEMBER 31, {YEAR}, BACKUP TO {RJ10/RJ60} AND SELECT 'YES'.}]
 ENTER DAY.

Responses: ----- 1 RJ120_03 (RJ1163)
 REFUSED ----- RF RJ120_03 (RJ1163)
 DON'T KNOW ----- DK RJ120_03 (RJ1163)

Programmer Instructions: Set JobStopDD

Display Instructions: Display RJ120_1, RJ120_2, and RJ120_3 on the same form pane. Display bracketed question text in lighter "grayed out" text.
 Display 'IF JOB ENDED... SELECT 'YES'.' if round 5. Otherwise, use a null display.
 Display 'RJ10' if looping on 'CURRENT-MAIN-JOB' (PR_JobTP=CURRENT MAIN).
 Display 'RJ60' if looping on 'CURRENT-MISCELLANEOUS-JOB-WITHIN- REFERENCE-PERIOD' (PR_JobTP=CURRENT MISC).'

Full Detail Spec

RJ130OS **(RJ1170)** **BLAISE NAME:** WhyLeftJobOS
Item Type: Question **Field kind:** Datafield **ArrayMin:** **Min value:**
Type Class: String **Field Size:** 25
Answer Type: {Continuous Answer.} **Answers allowed:** 1 **ArrayMax:** **Max value:**

Help Available () Show Card () Look Up File ()

Question Text:

SPECIFY: MAIN REASON

Responses: ----- 1 END_LP10 (RJ1175)
REFUSED ----- RF END_LP10 (RJ1175)
DON'T KNOW ----- DK END_LP10 (RJ1175)

Display Instructions: Display RJ130 and RJ130OS on the same form pane.

END_LP10 **(RJ1175)** **Item Type:** Route **Type Class:** End Loop

Route Details: Cycle on next job in the PERSON'S-JOBS-ROSTER that meets the conditions stated in the loop definition.
If no other jobs meet the stated conditions, end LOOP_10 and continue with BOX_70.

BOX_70 **(RJ1180)** **Item Type:** Route **Type Class:** If Then

Route Details: CONTINUE WITH EMPLOYMENT A SUBSECTION (EM).

[End of RJ]